


ifi

Accessory

iPurifier



1. SPDIF Output (coaxial)

Connect to the DAC or amplifier's co-axial digital input.


2. SPDIF Output (optical)

Connect to the DAC or amplifier's optical digital input.

Note: ONLY connect to one input. Do not connect to a coaxial input AND optical input simultaneously.


3. SPDIF Input (coaxial/optical)

Connect the digital output from the host (Apple TV, Google Chromecast, PS4, Xbox, CD transport etc).



4. LED

LED	Mode
Red	Unlock
Blue	44.1/48KHz
Magenta	88.2/96KHz
Cyan	176.4KHz
White	192KHz



5. Power input

The SPDIF iPurifier requires a clean 5V power supply to perform to the best of its ability. Please use the included iPower 5V, otherwise the performance of the SPDIF iPurifier will be hampered.

Note: Without a 5V power source, the SPDIF iPurifier will NOT function.

Technologies:

- Galvanic Isolation of SPDIF signal
 - REclock® and Regenerate®
 - <300 femto second(fs) Global Master Timing® master clock
 - Memory Buffer with flow control
 - Bit-Perfect operation, support up to 192kHz (PCM/DSD*), DTS, Dolby Digital and DoP* etc.
 - "Quieter than battery" Ultra clean iPower 5V included
- *DSD via DoP

Specifications:

- Supported Signals: 44.1/48/88.2/96/176.4/192kHz; 16 to 24 Bit, DSD/DoP, Dolby Digital, DTS
 - Input: Combo optical mini-jack & gold-plated coaxial connector (impedance 75 Ohms)
 - Outputs: gold-plated coaxial connector (impedance 75 Ohms) & optical mini-jack
 - Power Supply: micro USB, 5V/500mA (iPower 5V included)
 - Dimensions: 71(l) x 19(w) x 20(h)mm/ 2.8" x 0.74" x 0.79"
 - Weight: 29g (1.02oz)
 - Warranty period: 12 months
- Specifications are subject to change without notice.

ifi-audio.com

Ver1.1

ifi

warranty

In order to activate the warranty for this iFi product, you must register with the iFi website.

Component :

Serial no:

Terms & Conditions

ifi guarantees that this iFi product shall be free from defects in materials and workmanship for a period of 1 year for parts and labour.

The warranty period begins at the date of retail sale by an authorized iFi distributor/dealer and is subject to the following requirements and understandings:

- It is the responsibility of the buyer within 30 days from the original sale, to register and activate the product warranty with the iFi website.
- The original invoice must be produced for authentication prior to any warranty claim.
- The iFi product must not have been modified in any manner whatsoever, or the warranty will immediately become void.
- The iFi warranty is only valid in the country of original sale.
- The product must not have been stored in a humid environment; nor subjected to weather, water, or saltwater spray.
- iFi shall not, under any circumstances, be liable for any incidental or consequential damages arising from the loss of property or other damage or losses due to the failure of an iFi product. iFi is not liable for loss of use or inconvenience caused by the failure of an iFi product. iFi is not liable for damage caused to other audio components because of the failure of an iFi product.
- During the warranty period, iFi will repair the product to working order, or, at iFi's option, replace the defective module with a similar available product.
- All repairs performed after expiry of the warranty period will be charged to the owner and will carry a 180-day warranty on parts and labour. The customer is responsible for shipping the unit to the iFi distributor in the original packaging. This includes the payment of any shipping charges and related taxes.
- Should any warranty issues arise, the decision of iFi is full and final.

ifi-audio.com